



4-Battery Power Station Box

S-4010/S-4020/S-4030

- ◆ Install 4x V-mount batteries
- ◆ 2x XLR DC output (12V or 24V option)
- ◆ Real time output voltage LED display
- ◆ Low battery warning
- ◆ Charging without take out batteries
- ◆ Intelligent protective circuit design
- ◆ PP + Fiber glass case, strong and durable



<p>PP + Fiber glass case</p>	<p>Install 4x V-mount batteries</p>
<p>Inside charging (5A)</p>	<p>Voltage display / alert</p>

Output Descriptions:

S-4010 12v + 12v
Dual 12V output

4-pin XLR 11-16.8V DC output x2
Max Load: 15A/180W per channel
2 channels output simultaneously

S-4020 12v + 24v
12V + 24V output

4-pin XLR 11-16.8V DC output x1
Max Load: 15A/180W
3-pin XLR 22-33.6V DC output x1
Max Load: 15A/360W
12V and 24V will not output simultaneously

S-4030 24v + 24v
Dual 24V output

3-pin XLR 22-33.6V DC output x2
Max Load: 15A/360W in total
2 channels output simultaneously

Specification

Model	S-4010	S-4020	S-4030
Input	DC 16.8V 5A (Charging)	DC 16.8V 5A (Charging)	DC 16.8V 5A (Charging)
Output	DC11-16.8V 15Ax2 (180Wx2)	DC 11-16.8V 15A (180W) Or DC 22-33.6V 15A (360W)	DC 22-33.6V x2 Total 15A(360W)
Dimension	290mm x 221mm x 278mm		
Net weight	3.45Kg		
Working environment	Working temperature: 0°C ~ +40°C Working humidity: 10% ~ 90% Storage temperature: -15°C ~ + 60°C		

SWIT Electronics Co., Ltd.

Website: www.swit.cc Tel: +86 25 85805753
Email: contact@swit.cc Fax: +86 25 85805296

Distributed by: